

GRANDSTREAM WP810 Cordless IP Phone Configuration SOP-

Step 1: Wi-Fi से कनेक्ट करना और IP पता प्राप्त करना

1. सबसे पहले Cordless IP Phone (WP810) को उसी Wi-Fi नेटवर्क से कनेक्ट करें जिससे आपका Computer, Laptop या Mobile जुड़ा हुआ है।
2. फोन में जाएं:
Settings → **Network** → **Wi-Fi Networks**
और Status देखें।
3. यहां आपको IP Address दिखाई देगा (उदाहरण: 192.168.1.105)।
4. अब अपने Computer/Laptop/Mobile के किसी भी ब्राउज़र में यह IP Address टाइप करें और Enter दबाएं।
5. आपको Grandstream Web Login Page दिखाई देगा।
 - **Username:** admin
 - **Password:** फोन की battery निकालने के बाद पीछे की तरफ लिखा होता है।
6. Login करें।



Step 2: SIP Account Configuration

1. जाएं:
ACCOUNTS → **Account 1** → **General Settings**
2. निम्नलिखित सेटिंग्स करें:
 - **Account Active:** Yes

- **Account Name:** (उदा. Office Extension 101)
- **SIP Server:** (आपके PABX या IP Server का IP Address)
- **SIP User ID:** (Extension Number)
- **Authenticate ID:** (Extension Number या जैसा सर्वर पर हो)
- **Authenticate Password:** (Extension Password)
- **Name:** (User का नाम)

3. Save पर क्लिक करें।

The screenshot shows the Grandstream WP810 web interface. The browser address bar displays https://192.168.2.108/#page:account_1_general. The page title is "Grandstream WP810" and the user is logged in as "Admin". The main navigation menu includes "STATUS", "ACCOUNTS", "SETTINGS", "NETWORK", and "MAINTENANCE". The "ACCOUNTS" menu is expanded, showing "Account 1", "Account 2", and "Account Swap". The "Account 1" menu is further expanded to show "General Settings", "Network Settings", "SIP Settings", "Audio Settings", "Call Settings", "Intercom Settings", and "Feature Codes". The "General Settings" page for "Account 1" is displayed. The "Accounts" sidebar on the left shows "Account 1" selected. The "General Settings" section contains the following fields:

- Account Active: No Yes
- Account Name: 1060
- SIP Server: 103.162.132.11:9060
- Secondary SIP Server: (empty)
- Outbound Proxy: (empty)
- Backup Outbound Proxy: (empty)
- SIP User ID: 1060
- Authenticate ID: 1060
- Authenticate Password: (empty)
- Name: 1060
- Voice Mail Access Number: (empty)
- Account Display: User Name User ID

At the bottom of the form, there are three buttons: "Save", "Save and Apply", and "Reset". The "Save" button is highlighted with a green box. Green arrows point to the "Yes" radio button, the SIP Server field, the SIP User ID field, the Authenticate ID field, the Authenticate Password field, and the Name field.

Step 3: SIP Settings Configuration

1. जाएं:

ACCOUNTS → Account 1 → SIP Settings → Basic Settings

- निम्नलिखित सेटिंग्स करें:
 - OPTIONS Keep Alive Interval:** 15
 - SIP Transport:** TCP
- Save पर क्लिक करें।

The screenshot shows the Grandstream SIP Basic Settings page. The 'OPTIONS Keep Alive Interval' is set to 15, and 'SIP Transport' is set to TCP. A green arrow points to the interval field, and a green box highlights the transport options.

URL: https://192.168.2.108/#page:account_1_sip_basic_features

Navigation: STATUS ACCOUNTS SETTINGS NETWORK MAINTENANCE DIRECTORY

Account 1: General Settings, Network Settings, SIP Settings, Audio Settings, Call Settings, Intercom Settings, Feature Codes

Account 2: Custom SIP Headers, Advanced Features, Session Timer, Security Settings

Basic Settings

TEL URI: Disabled User=phone Enabled

SIP Registration: No Yes

Unregister on Reboot: No All Instance

Register Expiration: 60

Subscribe Expiration: 60

Reregister before Expiration: 0

Enable OPTIONS Keep Alive: No Yes

OPTIONS Keep Alive Interval: 15

OPTIONS Keep Alive Max Lost: 3

Enable TCP Keep Alive: No Yes

Local SIP Port: 9060

SIP Registration Failure Retry Wait Time: 20

SIP T1 Timeout: 0.5 sec

SIP T2 Timeout: 4 sec

SIP Timer B Timeout: 0

SIP Timer F Timeout: 0

SIP Transport: UDP TCP TLS/TCP

Step 4: Audio Settings Configuration

- जाएं:
ACCOUNTS → Account 1 → Audio Settings
- Preferred Vocoder – choice 1 to 7 सभी में OPUS चुनें।
- Save and Apply पर क्लिक करें।

https://192.168.2.108/#page:account_1_audio

Best Internet Servic... WhatsApp UISP | uisp.consamt... Online Business Ma... SAMS | OSMERP | St... UTC+2 time zone -...

Grandstream WP810 Admin Logout | Reboot English

GRANDSTREAM
CONNECTING THE WORLD

STATUS ACCOUNTS SETTINGS NETWORK MAINTENANCE DIRECTORY

Account 1 Account 2 Account Swap

General Settings Network Settings SIP Settings Audio Settings Call Settings Intercom Settings Feature Codes

Basic Settings Custom SIP Headers Advanced Features Session Timer Security Settings

Version 1.0.11.65

Audio Settings

Preferred Vocoder - choice 1	OPUS
Preferred Vocoder - choice 2	OPUS
Preferred Vocoder - choice 3	OPUS
Preferred Vocoder - choice 4	OPUS
Preferred Vocoder - choice 5	OPUS
Preferred Vocoder - choice 6	OPUS
Preferred Vocoder - choice 7	OPUS

Use first matching vocoder in 200OK SDP No Yes

On Hold Reminder Tone No Yes

Codec Negotiation Priority Caller Callee

Disable Multiple m line in SDP No Yes

Step 5: Registration Verification

1. जाएं:

STATUS → **Account Status**

2. देखें कि **SIP Registration** में

- Status: **YES**
- Indicator: **Green Color**

3. अगर **YES / Green** नहीं दिख रहा हो तो:

- **PABX Extension Number** और **Password** दोबारा चेक करें।
- गलत होने पर सही जानकारी डालकर **Save and Apply** करें।

Grandstream WP810 Admin Logout | Reboot English

GRANDSTREAM
CONNECTING THE WORLD

STATUS ACCOUNTS SETTINGS NETWORK MAINTENANCE DIRECTORY

Account Status
Network Status
System Info
Open Source Licenses

Version 1.0.11.65

Account Status

Account	SIP User ID	SIP Server	SIP Registration
Account 1	1080	103.162.132.11	YES
Account 2			UNKNOWN

Copyright © Grandstream Networks, Inc. 2025. All Rights Reserved.

✓ **Configuration Successful!**

अब आपका Grandstream WP810 Cordless IP Phone सफलतापूर्वक आपके PABX या SIP Server से रजिस्टर्ड हो गया है।